



STAGE V
COMPLIANT

PMi SERIES

inverter generators



FREEDOM OF movement



Camping, tailgating, feel outdoorsy. Time to power up your leisure experience and enjoy your home away from home with all comforts: appliances and personal electronics at your fingertips with no battery-dependent worries.

Optimal solution to combine silent operation with less fuel consumption and tension stability. They guarantee maximum efficiency through the Economy Mode, that automatically adjusts the engine speed to the optimum level to provide excellent fuel economy and noise reduction. The PMi Inverter Series has a compact design and are equipped with a handle that allows you to carry the product easily.

The range is equipped with a 12 Volt battery charger + cables, useful for recharging your car battery.

- Stable power for safe operation of sensitive electronics
- Pramac OHV engine
- Low oil level shutdown
- Economy mode for maximum fuel savings and noise reduction
- Ports for mobile electronics charging (USB and DC 12V)
- Digital display



INVERTER TECHNOLOGY: HOW DOES IT WORK?



The inverter technology improves the power quality. Inverter generators stabilize the output tension and provide high quality energy, which controls and stabilize the electrical supply. It is ideal for powering smart electronics, even computer and mobile phone.



PORTABILITY



DURABILITY



LOW NOISE



USB



RECOIL AND
ELECTRIC START



DIRECT
CURRENT



ATS CONNECTOR



REMOTE CONTROL



2 WIRE START

PMi 4500 EXCLUSIVE FEATURE

| | PMi 1000 | PMi 2500 | PMi 3000 | PMi 4500 |
|------------------------------|---|---|--------------------------------------|--------------------------------------|
| Single Phase Max Power | 950 Watts | 2300 Watts | 3000 Watts | 4200 Watts |
| Single Phase Rated Power | 850 Watts | 2000 Watts | 2800 Watts | 3800 Watts |
| Voltage | 230 V | 230 V | 230 V | 230 V |
| Running time at 50% load | 3.2 Hours | 3.6 hours | 6 Hours | 9.7 Hours Eco mode |
| Tank Capacity | 2.1 Litres | 3.5 Litres | 10 Litres | 12 Litres |
| Fuel consumption 50% (l/h) | 0.66 l/h | 0.9 l/h | 1.60 l/h | 1.20 l/h |
| Fuel | Petrol | Petrol | Petrol | Petrol |
| Displacement | 53 cc | 120.8 cc | 207 cc | 224 cc |
| Speed (rpm) | Variable | Variable | Variable | Variable |
| Starting System | Recoil | Recoil | Recoil | Electric+Recoil |
| Guaranteed sound level (LWA) | 89 LWA | 93 LWA | 96 LWA | 93 LWA |
| Noise emission at 7 m | 61 dB(A) | 67.7 dB(A) | 68 dB(A) | 68 dB(A) |
| Dimensions LxWxH (mm) | 480x250x395 | 535x305x460 | 555x400x450 | 578x422x500 |
| Dry Weight | 14 Kg | 22.5 Kg | 38 Kg | 42.5 Kg |
| Socket type Standard EU | 1 x Schuko 230V 16A 1 x DC 12V 6A n°2 USB 5V 2A | 2 x Schuko 230V 16A 1 x DC 12V 6A n°2 USB 5V 2A | 2 x Schuko 230V 16A 1 x DC 12V 6A | 2 x Schuko 230V 16A 1 x DC 12V 6A |
| Socket type UK | 1 x 230V 13A 3 Pin 1 x DC 12V 6A n°2 USB 5V 2A | 2 x 230V 13A 3 Pin 1 x DC 12V 6A n°2 USB 5V 2A | 2 x 230V 13A 3 Pin 1 x DC 12V 6A | |
| Battery charger | ✓ | ✓ | ✓ | ✓ |
| Economy Mode | ✓ | ✓ | ✓ | ✓ |
| Oil guard | ✓ | ✓ | ✓ | ✓ |
| Overload Protection | ✓ | ✓ | ✓ | ✓ |
| Hour meter | | ✓ | ✓ | ✓ |
| Volt meter | | ✓ | ✓ | ✓ |
| Frequency meter | | ✓ | ✓ | ✓ |
| Fuel level gauge | | | ✓ | ✓ |
| Wheel kit | | | ✓ | ✓ |
| 3xtra control | | | | ✓ |



www.pramac.com | www.pramacparts.com

The product images shown are for illustration purposes only and may not be an exact representation of the product. The manufacturer reserves the right to introduce changes to models and features without prior notice.
EN/04_2025_rev.2