

PMi Series

INVERTER GENERATOR



WE ARE **THE ENERGY** GENERATION!





Energy is **FREEDOM** for your family **NEEDS**

PRAMAC PMi SERIES INVERTER: optimal solution to combine silent operation with less fuel consumption and tension stability; the inverters Pramac stabilize the output tension and supply power for all kinds of equipment. They guarantee maximum efficiency through the Economy Mode, that automatically adjusts the engine speed to the optimum level to provide excellent fuel economy and noise reduction.

	FREQUENCY 50 Hz		
	PMi 1000	PMi 2000	PMi 3000
Single Phase Max Power	1000 Watts	2000 Watts	3000 Watts
Single Phase Rated Power	850 Watts	1700 Watts	2800 Watts
Voltage	230 V	230 V	230 V
Running time at 50% of load	3.2 Hours	3 Hours	6 Hours
Tank Capacity	2.1 Litres	3.5 Litres	10 Litres
Fuel	Petrol	Petrol	Petrol
Displacement	53 cc	113 cc	207 cc
Speed	Variable	Variable	Variable
Starting System	Recoil	Recoil	Recoil
Guaranteed sound level (LWA)	89 LWA	89 LWA	96 LWA
Noise emission at 7 m	61 dB(A)	61 dB(A)	68 dB(A)
Dimensions (mm) LxWxH	480x250x395	535x305x460	555x400x450
Dry Weight	14 Kg	22 Kg	38 Kg
Socket type	1 x Schuko 230V 16A 1 x DC 12V 6A n°2 USB 5V 2A	2 x Schuko 230V 16A 1 x DC 12V 6A n°2 USB 5V 2A	2 x Schuko 230V 16A 1 x DC 12V 6A
Oil guard	√	√	√
Fuel level gauge			√
Overload Protection	√	√	√
Hour meter		√	√
Volt meter		√	√
Frequency meter		√	√
Wheel kit			√
Battery charger	√	√	√
Economy Mode	√	√	√

Camping, tailgating, feel outdoorsy. Time to power up your leisure experience and enjoy your home away from home with all comforts: appliances and personal electronics at your fingertips with no battery-dependent worries.



PORTABILITY
PMi 1000
PMi 2000



PORTABILITY
PMi 3000

dB
GUARANTEE
NOISE
COMPLIANT



A) Control panel
B) Fuel tank cap with ventilation and priming pump

C) Starter level
D) Starter handle
E) ON/OFF switch contact





**WE ARE
THE ENERGY
GENERATION!**

Distributed by

For more information
visit us online at
www.pramac.com

PR INDUSTRIAL S.R.L.

Località Il Piano, 53031 Casole d'Elsa (SI) Italy
Tel. +39 0577 9651, Fax: +39 0577 949076
info@pramac.com / **www.pramac.com**

Worldwide Service & Parts
Online Center: **www.pramacparts.com**

© 2018 | PR INDUSTRIAL S.R.L. | All rights reserved
Image shown may not reflect actual package.
Specifications subject to change without notice.

